

CCS 1000 D Discussion Devices

www.boschsecurity.com



BOSCH
Invented for life



- ▶ Unique patent pending possible-to-speak indicator
- ▶ Plug and play functionality for ensuring fast installation and reconfiguration times
- ▶ Compact, attractive ergonomic design
- ▶ Easily configured as a participant device or chairperson's device
- ▶ Immunity to mobile phone interference

Discussion Devices are connected in a daisy-chain configuration to the Control Unit of a CCS 1000 Digital Discussion System. Their plug-and-play functionality allows them to be conveniently connected to and removed from the system as required. A power down or restart of the system is not necessary, which ensures for fast installation and reconfiguration times. Participants can take part in a discussion by speaking into the microphone and listening to proceedings through the built-in loudspeaker or (optional) headphones.

Functions

Possible-to-speak indication

A white possible-to-speak indicator above the microphone button indicates when the microphone can be activated.

Request-to-speak indication

A green request-to-speak indicator above the microphone button and in the head of the microphone indicate when a request-to-speak has been added to the waiting list. The indicators flash green when the request-to-speak is first in the waiting list.

Short or long microphone with flexible stem

The fixed microphone with flexible stem can be easily adjusted to suit the user. For maximum comfort, a short 310 mm (12.2 in) or long 480 mm (18.9 in) microphone stem is available.

Built-in loudspeaker with volume control

To ensure for optimum intelligibility, the loudspeaker volume of all Discussion Devices is centrally controlled from the Control Unit.

Face-to-face meeting feeling

An authentic face-to-face meeting feeling is achieved by allowing the loudspeaker and microphone to be on at the same time.

Headphones socket

The built-in 3.5 mm (0.14 in) stereo headphones socket enables the speaker to be clearly heard, even when there is excessive background noise.

Built-in volume control for headphones

For maximum comfort, the headphones volume can be adjusted by means of a rotary thumbwheel on the side of the Discussion Device. To prevent acoustic feedback from headphones to microphone, an option in the web browser application can be set to automatically reduce the headphones volume when the microphone is activated.

GSM immunity

Immunity to mobile phone interference ensures for clear, uninterrupted discussion.

Configurable as a participant or chairperson's device

The Discussion Device can be quickly configured as a 'chairperson's device', which enables a user to function as the chairperson at a meeting. No restart of the system is required. During a discussion, the chairperson can press and hold in the priority button to overrule all participant microphones. A chime is also sounded to announce that the chairperson is about to speak.

Controls and Indicators

- Microphone button
- Color-coded LED indicator above microphone button for showing the following states: microphone on, request-to-speak, and possible-to-speak
- Light-ring indicator in head of microphone
- Rotary thumbwheel on side of device for adjusting the headphones volume
- Concealed initialization button at base of device for reassigning the network address
- Concealed slide-switch at base of Discussion Device for configuring the Discussion Device as a 'participant Discussion Device' or 'chairperson's Discussion Device'
- Chairperson's configuration only – separate microphone button and 'priority button'

Connections

- 1 x 6-pole circular female connector with cable locking recess – for loop-through connection of Discussion Devices
- 1 x 3.5 mm (0.14 in) stereo headphones socket on side of device
- 1 x 2 m (78.7 in) cable with a 6-pole circular male connector with cable lock

Certifications and approvals

EU	CE, WEEE
US	FCC
CA	ICES-003
KR	KCC
AU/NZ	RCM
RU/KZ/BY	EAC
CN	China RoHS
SA	SASO

Installation/configuration notes

All Discussion Devices are delivered with a participant's microphone button, which can be easily exchanged for a set of chairperson's buttons. Two sets of chairperson's buttons and a special tool for removing the buttons are supplied with each Control Unit of a CCS 1000 Digital Discussion System. To

complete the configuration of the Discussion Device the concealed slide switch at the base of the Discussion Device has to be set from 'participant' to 'chairperson'.

Technical specifications**Electrical**

Frequency response	200 Hz to 12.5 kHz
Headphones load impedance	> 32 ohms < 1k ohm
Loudspeaker nominal output	72 dB SPL

Mechanical

Dimensions device without microphone (H x W x D)	64 x 203 x 146 mm (2.5 x 8.0 x 5.7 in)
Height with microphone in horizontal position	130 mm (5.1 in)
Length of microphone from mounting surface	CCSD-DS: 310 mm (12.2 in) CCSD-DL: 480 mm (18.9 in)
Weight	Approx. 1 kg (2.2 lb)
Mounting	Tabletop (portable or fixed)
Material (top)	Plastic ABS+PC
Material (base)	Metal ZnAl4
Color (top)	Traffic black (RAL 9017) matt-gloss
Color (base)	Pearl light grey (RAL 9022) matt-gloss

Environmental

Operating temperature	0 °C to +35 °C (+32 °F to +95 °F)
Storage temperature	-40 °C to +70 °C (-40 °F to +158 °F)
Relative humidity	15% to 90%
Air pressure	600 to 1100 hPa

Ordering information**CCS 1000 D Discussion Device Short**

Discussion Device for the CCS 1000 Digital Discussion System, supplied with short-stem fixed microphone, configurable as a delegate device or chairperson's device.

Order number **CCSD-DS**

CCS 1000 D Discussion Device Long

Discussion Device for the CCS 1000 Digital Discussion System, supplied with long-stem fixed microphone, configurable as a delegate device or chairperson's device.

Order number **CCSD-DL**

Represented by:

Americas:

Bosch Security Systems, Inc.
12000 Portland Avenue South
Burnsville MN 55337, USA
Phone: +1-800-392-3497
Fax: +1-800-955-6831
audiosupport@us.bosch.com
www.boschsecurity.com

Europe, Middle East, Africa:

Bosch Security Systems B.V.
P.O. Box 80002
5617 BA Eindhoven, The Netherlands
Phone: + 31 40 2577 284
Fax: +31 40 2577 330
emea.securitysystems@bosch.com
www.boschsecurity.com

Asia-Pacific:

Robert Bosch (SEA) Pte Ltd, Security
Systems
11 Bishan Street 21
Singapore 573943
Phone: +65 6571 2808
Fax: +65 6571 2699
apr.securitysystems@bosch.com
www.boschsecurity.asia

China:

Bosch (Shanghai) Security Systems Ltd.
201 Building, No. 333 Fuquan Road
North IBP
Changning District, Shanghai
200335 China
Phone +86 21 22181111
Fax: +86 21 22182398
www.boschsecurity.com.cn

America Latina:

Robert Bosch Ltda Security Systems Division
Via Anhanguera, Km 98
CEP 13065-900
Campinas, Sao Paulo, Brazil
Phone: +55 19 2103 2860
Fax: +55 19 2103 2862
latam.boschsecurity@bosch.com
www.boschsecurity.com

CCS 1000 D Control Units

www.boschsecurity.com



BOSCH
Invented for life



- ▶ Plug-and-play functionality for quick and easy connection of up to 80 Discussion Devices
- ▶ Intuitive web browser control for advanced configuration and control
- ▶ Built-in MP3 recorder with internal memory and USB recording
- ▶ Built-in Digital Acoustic Feedback Suppression (DAFS) for ensuring superior speech intelligibility
- ▶ Native support for automatic HD camera control

The Control Unit is the main component of the CCS 1000 Digital Discussion System. It supplies DC power to all connected Discussion Devices and monitors and controls the discussion system.

Touch-button control allows for easy configuration and operation of the unit, while intuitive LED indicators give a clear indication of the system settings.

Conveniently positioned connections at the rear of the unit enable peripheral equipment to be connected to the discussion system, such as audio equipment and Bosch HD Conference Domes.

Intuitive web browser control allows basic and advanced system settings to be easily viewed and changed, as required.

Two types of Control Unit are available:

- the CCSD-CU, and
- the CCSD-CURD that has additional features such as MP3 recording and Digital Acoustic Feedback Suppression (DAFS). The four RCA outputs at the rear of the CCSD-CURD ensure that the unit is optimized for use in courtrooms, i.e. for the recording of individual speakers.

Functions

Plug-and-play functionality

The plug-and-play functionality of the Control Unit allows Discussion Devices and system cameras to be conveniently connected to and removed from the system as required. A power down or restart of the system is not necessary, which ensures for fast installation and reconfiguration times.

Web browser control

Basic and advanced system settings, including microphone management and recording options, can be easily viewed and managed/configured by using a web browser in combination with a tablet, laptop or PC. Changes made in the web browser are automatically updated in the Control Unit and vice-versa. An option in the web browser allows the Control Unit and connected devices to be automatically shut down for energy saving purposes. To prevent unauthorized access to system settings, separate login rights are available for operators and technicians.

Open microphone control

The maximum number of microphones that can be activated by pressing the microphone buttons on the Discussion Devices can be selected with the 'Number of Open Microphones' (NOM) button on the Control

Unit. A maximum of four microphones can be selected on the Control Unit. This can be further extended to 10 microphones in the web browser.

Discussion control

One of the following microphone modes can be selected by pressing the 'Microphone-mode' button on the front of the Control Unit:

- **Open mode** – Participants can speak by pressing their microphone buttons. When the maximum number of open microphones is reached, the next participant that presses their microphone button is added to a waiting list. The first participant in the 'waiting list' is allowed to speak when an activated microphone is disabled.
- **Override mode** – Participants can override each other by pressing their microphone buttons. When the maximum number of open microphones is reached, the next participant that presses their microphone button will deactivate the microphone that has been activated for the longest time (the chairperson's microphone is not included in the number of open microphones and, therefore, cannot be overridden by a participant).
- **Voice activation mode** – Participants can activate their microphones by speaking into them. A microphone can be temporarily muted by pressing and holding down the microphone button.
- **Push to talk (PTT) mode** – Participants can speak by pushing and holding in their microphone buttons. The microphone is deactivated when the microphone button is released. The maximum number of participants that can speak is determined by the number of open microphones.

Interface for peripheral equipment

The Control Unit enables the following equipment to be connected to the CCS 1000 Digital Discussion System:

- System cameras – for giving a clear visual overview of the proceedings. A maximum of six Bosch HD Conference Dome cameras can be connected to the system with native support (the camera presets can be configured in the web browser).
- External wired or wireless microphone – to allow a guest speaker or an audience to participate in a discussion
- Sound reinforcement system – for transmitting the proceedings to an audience in the same room or an adjacent room
- Audio equipment – for broadcasting music through the loudspeakers of the discussion system
- External audio processor – for modifying the floor signal distributed to the participant loudspeakers and headphones (i.e. equalizing)
- Telephone coupler – to allow a remote participant to join a discussion via a telephone/video connection
- External recorder – for recording and playing back discussions
- Computer (connected via micro USB connector at rear of Control Unit) – for transferring recordings (discussions) from the internal memory of the Control Unit

Built-in MP3 recorder

(CCSD-CURD only)

The built-in recorder can record discussions in the MP3 format to the internal memory or a USB memory stick with a maximum capacity of 128 GB, which can store up to 4,000 hours discussion. To ensure that discussions are manageable, recordings are divided into files of one hour's duration containing the date and time of recording.

- **Internal memory** – recordings are automatically saved in the internal memory unless a USB memory stick is connected to the USB connector at the front of the Control Unit. The internal memory can record up to 8 hours discussion.
- **USB memory stick** – recordings are automatically saved to a USB memory stick when it is connected to the Control Unit. A USB memory stick of 128 GB can record up to 4,000 hours discussion.

LED indicators inform users when data is being recorded to the internal memory or USB memory stick. Three short beeps and a red flashing LED indicate when 5 minutes of recording are left. A long beep and a red/green flashing LED indicate when it is not possible to record a discussion (i.e. internal memory full and USB memory stick not connected to the Control Unit, USB memory stick full or damaged).

Built-in monitor loudspeaker

(CCSD-CURD only)

The built-in loudspeaker and headphone socket allows for:

- live monitoring of a meeting from the CCSD-CURD Control Unit
- prelistening of audio files before replaying them to the Floor.

Built-in Digital Acoustic Feedback Suppression (DAFS)

(CCSD-CURD only)

The built-in Digital Acoustic Feedback Suppression (DAFS) feature suppresses acoustic feedback (also known as 'howling' or 'Larsen effect'). This improves speech intelligibility by allowing the speaker volume to be set as loud as required without any risk of acoustic feedback.

Controls and Indicators

- Mains power on/off button with red/green LED indicator. Red indicates that the system is off (no power available from the external power supply). Green indicates that the system is active (Control Unit and all connected devices powered up).
- Plus/minus buttons for setting the volume range of all connected Discussion Devices – used in combination with LED indicators for showing the selected volume
- Microphone-mode button for selecting one of the microphone operating modes – used in combination with LED indicators for showing the selected mode
- Open microphone button for selecting the number of microphones that can be activated at the same time – used in combination with LED indicators for showing the number of activated microphones

(CCSD-CURD only)

- Plus/minus buttons for setting the volume of the built-in loudspeaker or headphones, if connected – used in combination with LED indicators for showing the selected volume
- Combined record/pause button for starting and pausing a recording session
- Stop recording button for ending a recording session
- Internal recording LED indicator, and USB recording LED indicator

Connections

Front of unit (CCSD-CURD only):

- 1 x 3.5 mm (0.14 in) stereo headphone socket
- 1 x USB connector

Rear of unit:

- 1 x micro USB connector (CCSD-CURD only)
- 4 x RCA outputs for individual microphone recording, e.g. for recording individual speakers in a courtroom (CCSD-CURD only)
- 1 x 4-pole circular female 24 VDC power input connector
- 2 x 6-pole circular female connectors for loop-through connection of 40 Discussion Devices per trunk
- 1 x RJ45 Ethernet connector for communication with web browser application
- 1 x 3-pole XLR female microphone input connector with phantom supply
- 1 x RCA input for 'Floor' (i.e. external audio source, such as a CD or DVD player)
- 1 x RCA output for a 'sound reinforcement system'
- 1 x RCA input/output for either:
 - 'Recorder' for connecting an external recorder
 - 'Insertion' for connecting an external audio processor
 - 'Telephone/mix minus' for allowing a remote participant to join a discussion via a telephone/video connection
 - 'Participant loudspeaker' for distributing the participant loudspeaker signal to a sound reinforcement system

Only one piece of audio equipment can be connected to this RCA input/output at any one time. The RCA input/output has to be configured by selecting the required option in the web browser.

Certifications and approvals

EU	CE, WEEE ¹
US	UL, FCC
CA	CSA, ICES-003, EPS ¹
KR	KCC, KC ¹ , K-MEPS ¹
AU/NZ	RCM, MEPS ¹
RU/KZ/BY	EAC
JP	PSE ¹
CN	China RoHS, CCC ¹

TW	BSMI ¹
SA	SASO

Note: ¹ Only applicable for the power adaptor.

Region	Certification
Europe	CE

Parts included

Quantity	Component
1	CCSD-CU Control Unit or CCSD-CURD Control Unit
1	Mains power cord
1	24 VDC power supply
2	Sets of chairperson's buttons for the Discussion Device
1	Exchange tool for buttons
1	Set of feet for table top use
1	Set of 19" 1U mounting brackets
1	Safety instructions
1	DVD with operation manual and supporting tools

Technical specifications

Electrical

Mains voltage	100 to 240 VAC ± 10%
Current consumption	Maximum 0.6 A (100 VAC) to 0.2 A (240 VAC)
DC supply to Discussion Devices	24 V ± 1 V (current limited)
Number of Discussion Devices per Control Unit	Max. 40 devices per trunk connector
Discussion Device loudspeakers volume control	15 steps of 1.5 dB (starting from -10.5 dB)
Limit threshold level to unit	12 dB above nominal level
Gain reduction due to number of open microphones (NOM)	1/SQRT (NOM)
Sample rate	44.1 kHz

Total harmonics

Nominal input (85 dB SPL)	< 0.5%
Max. input (110 dB SPL)	< 0.5%

Audio inputs

XLR nominal microphone input	-56 dBV
XLR maximum microphone input	-26 dBV
RCA nominal input	-24 dBV (+/- 6 dB)
RCA maximum input	+6 dBV

S/N	> 94 dBA
Frequency response	30 Hz to 20 kHz

Audio outputs

RCA nominal output	-24 dBV (+6/- 24 dB)
RCA maximum output	+6 dBV
S/N	> 102 dBA
Frequency response	30 Hz to 20 kHz

Recorder (CCSD-CURD)

Recording/ Playback (bit rate)	64, 96, 128, 256 Kbit/sec
Recording/ Playback (sample frequency)	44.1 kHz

Monitoring loudspeaker (CCSD-CURD)

Nominal output	72 dB SPL
Frequency response	200 Hz to 12.5 kHz
Gain range mute	-10.5 to +12

USB memory stick compatibility (CCSD-CURD)

SanDisk USB memory stick	Formatted with FAT32 file system. Maximum size: 128 GB.
--------------------------	--

Recording capacity in hours (CCSD-CURD)

Bite rate	Internal memory hours	USB memory stick hours			
		16 GB	32 GB	64 GB	128 GB
64	8 hrs	500	1000	2000	4000
96	5 hrs	350	700	1400	2800
128	4 hrs	250	500	1000	2000
256*	2 hrs	125	250	500	1000

* Supported when recording floor only.

Mechanical

Dimensions including feet (H x W x D)	45 x 440 x 200 mm (1.8 x 17.3 x 7.9 in) 19" wide, 1 RU high
Height of feet	5.5 mm (0.2 in)
Mounting	Tabletop 19-inch rack
Weight (CCSD-CU)	Approx. 3.2 kg (7.1 lb)
Weight (CCSD-CURD)	Approx. 3.4 kg (7.5 lb)
Material (top)	Painted metal
Material (base)	Painted metal
Color (top)	Traffic black (RAL 9017) matt-gloss

Color (base)	Traffic black (RAL 9017) matt-gloss
Rim	Pearl light grey (RAL 9022) matt-gloss

Environmental

Operating temperature	5 °C to +45 °C (+41 °F to +113 °F)
Storage temperature	-40 °C to +70 °C (-40 °F to +158 °F)
Relative humidity	5% to 98% non-condensing

Ordering information**CCS 1000 D Control Unit**

Control Unit for the CCS 1000 Digital Discussion System, provides power for the Discussion Devices, enables peripheral equipment to be connected to the discussion system.

Order number **CCSD-CU**

CCS 1000 D Control Unit Recorder DAFS

Control Unit for the CCS 1000 Digital Discussion System, has MP3 recording and DAFS, provides power for the Discussion Devices, enables peripheral equipment to be connected to the discussion system.

Order number **CCSD-CURD**

Represented by:

Americas:

Bosch Security Systems, Inc.
12000 Portland Avenue South
Burnsville MN 55337, USA
Phone: +1-800-392-3497
Fax: +1-800-955-6831
audiosupport@us.bosch.com
www.boschsecurity.com

Europe, Middle East, Africa:

Bosch Security Systems B.V.
P.O. Box 80002
5617 BA Eindhoven, The Netherlands
Phone: + 31 40 2577 284
Fax: +31 40 2577 330
emea.securitysystems@bosch.com
www.boschsecurity.com

Asia-Pacific:

Robert Bosch (SEA) Pte Ltd, Security
Systems
11 Bishan Street 21
Singapore 573943
Phone: +65 6571 2808
Fax: +65 6571 2699
apr.securitysystems@bosch.com
www.boschsecurity.asia

China:

Bosch (Shanghai) Security Systems Ltd.
201 Building, No. 333 Fuquan Road
North IBP
Changning District, Shanghai
200335 China
Phone +86 21 22181111
Fax: +86 21 22182398
www.boschsecurity.com.cn

America Latina:

Robert Bosch Ltda Security Systems Division
Via Anhanguera, Km 98
CEP 13065-900
Campinas, Sao Paulo, Brazil
Phone: +55 19 2103 2860
Fax: +55 19 2103 2862
latam.boschsecurity@bosch.com
www.boschsecurity.com